



ITEM	P/N	QTY.	DESCRIPTION
37	20616	1	LAMP, T5, 14W 22IN
36	20609	2	LAMP HOLDER
35	20607	1	BALLAST
34	23777	3	TERMINAL, MALE, 1/4", FULLY INSULATED
33	23784	3	TERMINAL, FEMALE, 1/4", FULLY INSULATED
32	-----	---	-----
31	-----	---	-----
30	20370	1	RECEPTACLE, NEMA 15-50R, 50A, 3PH
30	22775	1	RECEPTACLE, NEMA 6-50R, 50A, 1PH
29	20397	1	LINE FILTER
28	20318	1	RELAY, 208-240V
27	20312	1	RELAY BASE
26	23173	1	SWITCH, N.O., MOMENTARY
25	20670	2	TERMINAL_BLOCK, GRND, AWG 6-20
24	20669	4	TERMINAL_BLOCK, 73 AMP, AWG 6-20
23	20304	1	GROUND_BLOCK, 4-12 GA WIRE
22	20303	5	TERMINAL_BLOCK, 4-12 GA WIRE
21	20399	1	INDICATOR_LIGHT, AMBER, 250V, 1/2 WATT
20	20398	1	INDICATOR_LIGHT, GREEN, 250V, 1/2 WATT
19	90226	1	LAMP, 16", UV, REPLACEMENT ONLY
18	20373	1	BALLAST/LAMP ASSY, COMPLETE, 16"
17	21875	2	FUSE 6A
16	20411	2	FUSEHOLDER
15	22950	1	SONALERT, E.A.C.
14	23782	1	SONALERT, CLOGGED FILTER
13	23776	1	MODULE, AIR FILTER
12	20473	1	PRESSURE_SWITCH, DUNGS, 0.4-4" WC
11	24209	1	LED
10	21157	1	SWITCH, LIMIT, OMRON
9	25275	3	WIRE NUT (BLUE)
8	21190	1	SWITCH, POWER (ROCKER)
7	21151	1	CONTACTOR, 63AMP RES, 3PH
6	35864	1	FAN, ASSY, 208-240/60/1 (PO-VH)
5	23751	1	TERMINAL_BLOCK
4	20402	2	INDICATOR_LIGHT, RED, 250V, 1/2 WATT
3	24237	2	SWITCH, MICRO (PLUNGER)
2	24208	1	POWER_SUPPLY
1	21125	1	CONTACT_BOARD

-3 PH WITH RECT ONLY
 -1 PH WITH RECT ONLY
 -ILS ONLY
 -ILS ONLY
 -ILS ONLY
 -UV ONLY
 -UV ONLY

NOTE: UNLESS OTHERWISE NOTED ALL WIRES ARE 18 GAUGE.

NOTE: A GREEN/YELLOW GND. STRAP MUST BE CONNECTED BETWEEN THE PART AND THE UNIT'S CHASSIS.

FOR SUPPLY POWER- USE ONLY 8 GA. COPPER WIRE
 REMOVE JUMPERS IF HOOD POWER IS DIFFERENT THAN FRYER POWER.

HOOD POWER- IF DIFFERENT THAN APPLIANCE POWER ONLY- REMOVE JUMPERS
 CONTACTOR COIL- USED WHEN USING MULTIPLE APPLIANCES UNDER HOOD
 SWITCH- FIRE EXTINGUISHER SYSTEM (USED TO SHUT DOWN APPLIANCE POWER)

REMOVE BOTH JUMPERS IF HOOD POWER IS DIFFERENT THAN APPLIANCE POWER.

WIRING DIAGRAM GVH-C/F
 (UV/ILS/CE/RECEPT OPTIONAL) 208-240/60/1